arXiv:1502.02752v1 [nlin.SI] 10 Feb 2015

On an integrable system related to the relativistic Toda lattice -Bäcklund transformation and integrable discretization

Luc Vinet[†], Guo-Fu Yu[‡] *and Ying-Nan Zhang[§,♯]

[†] Centre de Recherches Mathématiques, Université de Montréal,
C.P.6128, Centre-ville Station, Montréal, Québec, H3C 3J7, Canada
[‡]Department of Mathematics, Shanghai Jiao Tong University,
Shanghai 200240, P.R. China
[§]LSEC, Institute of Computational Mathematics and Scientific Engineering Computing,
Academy of Mathematics and System Sciences,
Chinese Academy of Sciences, P.O. Box 2719, Beijing 100080, P.R. China
[♯]Graduate School of the Chinese Academy of Sciences, Beijing, P.R. China

Abstract

We study an integrable system related to the relativistic Toda lattice. The bilinear representation of this lattice is given and the Bäckulund transformation obtained. A fully discrete version is also introduced with its bilinear Bäcklund transformation and Lax pair. One-soliton solution of the discrete system is presented by use of Bäcklund transformation.

Keywords: relativistic Toda lattice, integrable discretization, bilinear method, Bäcklund transformation

1 Introduction

In terms of the canonical variables $\{q_n, \Theta_n\}_{n\in Z}$, the Hamiltonian for the infinite relativistic Toda lattice (RTL) is given by [1, 2]

$$H(q,\Theta) = \sum_{n\in Z}\{\exp(\Theta_n)[1+\exp(q_{n-1}-q_n)]^{1/2}\times[1+\exp(q_n-q_{n+1})]^{1/2}-2\}. \tag{1.1}$$

The equations of motion are hence

$$\frac{d}{dt}q_n = \frac{\partial H_n}{\partial \Theta_n} = b_n, \tag{1.2}$$

$$\frac{d}{dt}\Theta_n = -\frac{\partial H_n}{\partial q_n} = \frac{1}{2}a_{n-1}(b_n+b_{n-1}) - \frac{1}{2}a_n(b_n+b_{n+1}), \tag{1.3}$$

with

$$b_n = \exp(\Theta_n)[1+\exp(q_{n-1}-q_n)]^{1/2}\times[1+\exp(q_n-q_{n+1})], \tag{1.4}$$

$$a_n = \frac{\exp(q_n-q_{n+1})}{1+\exp(q_n-q_{n+1})}. \tag{1.5}$$

---

*Corresponding author: gfyu@sjtu.edu.cn

The RT equation

$$\begin{aligned}\ddot{q}_n =&(1+\frac{1}{c}\dot{q}_{n-1})(1+\frac{1}{c}\dot{q}_n)\frac{\exp(q_{n-1}-q_n)}{1+(1/c^2)\exp(q_{n-1}-q_n)}\\ &-(1+\frac{1}{c}\dot{q}_n)(1+\frac{1}{c}\dot{q}_{n+1})\frac{\exp(q_n-q_{n+1})}{1+(1/c^2)\exp(q_n-q_{n+1})},\end{aligned} \tag{1.6}$$

where q_n is the coordinates of $n-$th lattice point, and means the differentiation with respect to time t and c is the light speed, was introduced and studied by Ruijsenaars [3]. The evolution equations of $\{a_n, b_n\}$ assume the form

$$\frac{d}{dt}b_n = b_n(b_{n-1}a_{n-1} - a_n b_{n+1}), \tag{1.7}$$
$$\frac{d}{dt}a_n = a_n(1-a_n)(b_n - b_{n+1}). \tag{1.8}$$

By a further transformation

$$u_n = b_n(1-a_n), \quad v_n = a_n b_n, \tag{1.9}$$

the equations (1.7)-(1.8) are rewritten as

$$\frac{d}{dt}u_n = u_n(v_{n-1} - v_n), \tag{1.10}$$
$$\frac{d}{dt}v_n = v_n(v_{n-1} - v_{n+1} + u_n - u_{n+1}). \tag{1.11}$$

We refer to (1.10)-(1.11) as the RTL. [2, 4, 5].

The integrable lattice equations are related to the following discrete spectrum problem and time evolution equation

$$E\varphi_n = U_n(u,\lambda)\varphi_n, \tag{1.12}$$
$$\varphi_{n,t} = V_n(u,\lambda)\varphi_n, \tag{1.13}$$

where u is the potential function, λ the spectral parameter and E the shift operator defined by $Ef_n = f_{n+1}$.

The integrability condition between (1.12) and (1.13) leads to the integrable lattice system

$$U_{n,t} + U_n V_n - V_{n+1}U_n = 0, \tag{1.14}$$

when we take $u = (u_n, v_n)^T$, and

$$U_n = \begin{pmatrix} \lambda^2 + u_n & \lambda \\ \lambda v_n & 0 \end{pmatrix} \tag{1.15}$$
$$V_n = \begin{pmatrix} \lambda^2/2 - v_{n-1} & \lambda \\ \lambda v_{n-1} & -\lambda^2/2 - u_n - v_n \end{pmatrix}. \tag{1.16}$$

The compatibility condition (1.14) entails the RTL equation (1.10)-(1.11). So (1.12) and (1.13) with (1.15)-(1.16) constitute a Lax pair for the RTL (1.10)-(1.11). Other Lax presentation for (1.10)-(1.11) can be found in [5–8]. The bilinear form and Casorati determinant solution for the RTL (1.6) were given in [9]. It is also worth pointing out that the RTL (1.10)-(1.11) can be related to the Laurent bi-orthogonal polynomials [10, 11]. The discretization of the RTL (1.6) was first performed in [12] using the Hamiltonian method. The discrete-time relativistic Toda lattice (dRTL) equation was first proposed by Suris

$$\frac{\delta\exp(q_n^{t+1}-q_n^t)-1}{\delta\exp(q_n^t-q_n^{t-1})-1} = \frac{1+g^2\exp(q_{n-1}^t-q_n^t)}{1+g^2\exp(q_n^t-q_{n+1}^t)}\frac{1+(g^2/\delta)\exp(q_n^t-q_{n+1}^{t+1})}{1+(g^2/\delta)\exp(q_{n-1}^{t-1}-q_n^t)}. \tag{1.17}$$

The Lagrangian form of dRTL was presented in [13]. The Casorati determinant solution for the discrete RT lattice (1.17) was given in [14] and the elliptic solutions in [15].

Although the discrete version of the RTL (1.6) is already known, as far as we know, the discrete analogue of the RTL related system (1.10)-(1.11) has not been given. The purpose of this paper is to propose a direct discrete version of the RTL (1.10)-(1.11) using Hirota bilinear method. It is nontrivial and of considerable interest to find integrable discretizations for integrable equations. Attention is being paid to the problem of integrable discretizations of integrable systems. (See e.g., [16–20] and references therein). Various approaches to the problem of integrable discretization are currently available. One of them is Hirota's bilinear method [21–26], which is based on gauge invariance and soliton solutions. Here, we focus on a discretization process such that the resulting discrete bilinear equations have Bäcklund transformations (BTs). As a bonus, we can usually derive Lax pairs for the resulting discrete equations. This method has been successfully applied to the discretization of $(2+1)$-dimensional sinh-Gordon equation [27] and of the two dimensional Leznov lattice equation [28]. Based on bilinear forms and determinant structure of solutions, Hirota's discretization method has also been developed to construct discrete versions of the Camassa-Holm equation [29] and the short pulse equation [30].

The content of the paper is organized as follows. In section 2, we give a bilinear form of the RTL. In section 3, a BT and Lax pair are exhibited. In section 4 an integrable discretization of the RTL is presented and the integrability is made manifest by the corresponding BT. Section 5 is devoted to conclusion and discussions.

2 Bilinear form for the RTL

Performing the change of the dependent variable

$$v_n = \frac{d}{dt}\ln\frac{F_n}{G_n} + 1, \qquad u_n = \frac{d}{dt}\ln\frac{G_{n-1}}{F_n} + 1, \tag{2.1}$$

the system (1.10)-(1.11) is transformed into the following bilinear form

$$D_t G_{n-1}\bullet F_n + F_n G_{n-1} = c_1 F_{n-1} G_n, \tag{2.2}$$

$$D_t F_n \bullet G_n + F_n G_n = c_2 F_{n-1} G_{n+1}, \tag{2.3}$$

which can also be written as follows in terms of the Hirota bilinear differential:

$$(D_t e^{\frac{1}{2}D_n} - e^{\frac{1}{2}D_n} + c_1 e^{-\frac{1}{2}D_n}) F\bullet G = 0, \tag{2.4}$$

$$(D_t + 1 - c_2 e^{-D_n}) F\bullet G = 0. \tag{2.5}$$

Here c_1, c_2 are arbitrary constants. In the following we shall take $c_1 = c_2 = 1$ for simplicity. The Hirota bilinear differential operator D_t^k and the bilinear difference operator $\exp(\delta D_n)$ are respectively defined [31] by

$$D_t^k a\bullet b \equiv \left(\frac{\partial}{\partial t} - \frac{\partial}{\partial t'}\right)^k a(t)b(t')|_{t'=t},$$

$$\exp(\delta D_n) a(n)\bullet b(n) \equiv a(n+\delta)b(n-\delta).$$

It is well known that nonlinear integrable equations share many common features, among which, the BT and their associated nonlinear superposition formulae [32–35].

3 Bilinear Bäcklund transformation for the RTL

For the sake of convenience, we introduce an additional discrete variable m and set

$$F = f_{m+\frac{1}{2}}, \quad G = f_{m-\frac{1}{2}} \tag{3.1}$$

We shall denote $F(t,n)$ by F_n and $f(t,n,m)$ by $f_{n,m}$ for simplicity. With the help of (3.1), the eqs. (2.2), (2.3) reduce to

$$(D_t e^{\frac{D_n + D_m}{2}} - e^{\frac{D_n + D_m}{2}} + e^{\frac{D_m - D_n}{2}}) f\bullet f = 0, \tag{3.2}$$

$$(D_t e^{\frac{D_m}{2}} + e^{\frac{D_m}{2}} - e^{\frac{D_m}{2} - D_n}) f\bullet f = 0. \tag{3.3}$$

Proposition 3.1 *The bilinear equations (3.2), (3.3) have the Bäcklund transformation*

$$(D_t - \lambda e^{-D_n} + \mu) f \bullet g = 0, \tag{3.4}$$

$$(e^{\frac{D_n-D_m}{2}} - e^{\frac{D_m-D_n}{2}} - \lambda e^{-\frac{D_n+D_m}{2}}) f \bullet g = 0, \tag{3.5}$$

$$(\lambda e^{-D_n-\frac{D_m}{2}} + e^{-\frac{D_m}{2}} + \gamma e^{\frac{D_m}{2}}) f \bullet g = 0, \tag{3.6}$$

where λ, μ and γ are arbitrary constants.

Proof. Let f be a solution of equations (3.2)-(3.3). If it can be shown that g given by (3.4)-(3.6) satisfies

$$\begin{aligned} P_1 &\equiv (D_t e^{\frac{D_n+D_m}{2}} - e^{\frac{D_n+D_m}{2}} + e^{\frac{D_m-D_n}{2}}) g \bullet g = 0, \\ P_2 &\equiv (D_t e^{\frac{D_m}{2}} + e^{\frac{D_m}{2}} - e^{\frac{D_m}{2}-D_n}) g \bullet g = 0, \end{aligned}$$

then the equations (3.4)-(3.6) define a BT for (3.2)-(3.3).

In fact, using (3.4)-(3.6) and the bilinear identities, it can be seen that

$$\begin{aligned} &-[e^{\frac{D_m}{2}} f \bullet f] P_2 \\ &\equiv [(D_t e^{\frac{D_m}{2}} + e^{\frac{D_m}{2}} - e^{\frac{D_m}{2}-D_n}) f \bullet f][e^{\frac{D_m}{2}} g \bullet g] - [(D_t e^{\frac{D_m}{2}} + e^{\frac{D_m}{2}} - e^{\frac{D_m}{2}-D_n}) g \bullet g][e^{\frac{D_m}{2}} f \bullet f] \\ &= 2\sinh(\frac{D_m}{2})[D_t f \bullet g] \bullet (fg) - 2\sinh(\frac{D_n}{2})(e^{\frac{D_n-D_m}{2}} f \bullet g) \bullet (e^{\frac{D_m-D_n}{2}} f \bullet g) \\ &= 2\sinh(\frac{D_m}{2})[D_t f \bullet g] \bullet (fg) + 2\lambda \sinh(\frac{D_m}{2})(fg) \bullet (e^{-D_n} f \bullet g) \\ &= 2\sinh(\frac{D_m}{2})[(D_t - \lambda e^{-D_n}) f \bullet g] \bullet (fg) \\ &= 0 \end{aligned}$$

$$\begin{aligned} &-[e^{\frac{D_m+D_n}{2}} f \bullet f] P_1 \\ &\equiv [(D_t e^{\frac{D_n+D_m}{2}} - e^{\frac{D_n+D_m}{2}} + e^{\frac{D_m-D_n}{2}}) f \bullet f][e^{\frac{D_m+D_n}{2}} g \bullet g] \\ &\qquad - [(D_t e^{\frac{D_n+D_m}{2}} - e^{\frac{D_n+D_m}{2}} + e^{\frac{D_m-D_n}{2}}) g \bullet g][e^{\frac{D_m+D_n}{2}} f \bullet f] \\ &= 2\sinh(\frac{D_m+D_n}{2})(D_t f \bullet g) \bullet (fg) - 2\sinh(\frac{D_n}{2})(e^{\frac{D_m}{2}} f \bullet g) \bullet (e^{-\frac{D_m}{2}} f \bullet g) \\ &= 2\sinh(\frac{D_m+D_n}{2})(\lambda e^{-D_n} f \bullet g) \bullet (fg) - 2\sinh(\frac{D_n}{2})(e^{\frac{D_m}{2}} f \bullet g) \bullet (e^{-\frac{D_m}{2}} f \bullet g) \\ &= 2\sinh(\frac{D_n}{2})(e^{\frac{D_m}{2}} f \bullet g) \bullet [(-\lambda e^{-D_n-\frac{D_m}{2}} - e^{-\frac{D_m}{2}}) f \bullet g] \\ &= 0. \end{aligned}$$

This completes the proof of proposition 2.1.

From Proposition 2.1 it can be deduced that the bilinear RTL (3.2)-(3.3) has the following Bäcklund transformation:

$$D_t F \bullet F' - \lambda F_{n-1} F'_{n+1} + \mu F F' = 0, \tag{3.7}$$

$$D_t G \bullet G' - \lambda G_{n-1} G'_{n+1} + \mu G G' = 0, \tag{3.8}$$

$$G_{n+1} F' - F G'_{n+1} - \lambda G F'_{n+1} = 0, \tag{3.9}$$

$$\lambda G_{n-1} F'_{n+1} + G F' + \gamma F G' = 0, \tag{3.10}$$

where F' and G' are defined by

$$F' = g_{m+\frac{1}{2}}, \qquad G' = g_{m-\frac{1}{2}}. \tag{3.11}$$

Starting from the bilinear BT (3.7)-(3.10), we can derive a Lax pair for the system (1.10)-(1.11). First, set

$$\Phi_n = \frac{F_n}{F'_n}, \quad \Psi_n = \frac{G_n}{G'_n}, \quad P_n = \ln \frac{G'_{n-1}}{F'_n}, \quad Q_n = \ln \frac{F'_n}{G'_n}$$

in (3.7)-(3.10). Eqs (3.7)-(3.10) are then transformed into

$$\Psi_{n,t} - \lambda e^{P_n+Q_n-P_{n+1}-Q_{n+1}}\Psi_{n-1} + \mu\Psi_n = 0, \tag{3.12}$$

$$\Phi_{n,t} - \lambda e^{P_n+Q_{n-1}-P_{n+1}-Q_n}\Phi_{n-1} + \mu\Phi_n = 0, \tag{3.13}$$

$$\Psi_{n+1} - \Phi_n - \lambda e^{Q_{n+1}-Q_n}\Psi_n = 0, \tag{3.14}$$

$$\Psi_n + \gamma\Phi_n + \lambda e^{P_n-P_{n+1}}\Psi_{n-1} = 0. \tag{3.15}$$

From the compatibility of above equations we now obtain

$$\frac{d}{dt}P_n - e^{Q_{n-1}-Q_n} = \frac{d}{dt}P_{n+1} - e^{Q_n-Q_{n+1}}, \tag{3.16}$$

$$\frac{d}{dt}Q_n - e^{P_n-P_{n+1}+Q_{n-1}-Q_{n+1}} = \frac{d}{dt}Q_{n+1} - e^{P_{n+1}-P_{n+2}+Q_n-Q_{n+2}}, \tag{3.17}$$

so we have

$$\frac{d}{dt}P_n = e^{Q_{n-1}-Q_n} + c_1, \tag{3.18}$$

$$\frac{d}{dt}Q_n = e^{P_n-P_{n+1}+Q_{n-1}-Q_{n+1}} + c_2, \tag{3.19}$$

Here c_1, c_2 are two arbitrary constants. We now introduce the new potentials $u_n = P_{n,t} - c_1, v_n = Q_{n,t} - c_2$ and differentiate Eqs. (3.18) and (3.19) to find

$$\frac{d}{dt}u_n = e^{Q_{n-1}-Q_n}(v_{n-1} - v_n) = u_n(v_{n-1} - v_n), \tag{3.20}$$

$$\begin{aligned}\frac{d}{dt}v_n &= e^{P_n-P_{n+1}+Q_{n-1}-Q_{n+1}}(u_n - u_{n+1} + v_{n-1} - v_{n+1}) \\ &= v_n(u_n - u_{n+1} + v_{n-1} - v_{n+1}),\end{aligned} \tag{3.21}$$

which is the original nonlinear RT lattice (1.10) and (1.11). So (3.12)-(3.15) provide a Lax pair for RTL (1.10)-(1.11).

Using (3.7)-(3.10), we can obtain a nontrivial solution from the trivial solution. It is easy to check that $F' = G' = 1$ is a solution of (2.2)-(2.3). Substituting this trivial solution into the BT (3.7)-(3.10), we have

$$F_t - \lambda F_{n-1} + \mu F_n = 0, \tag{3.22}$$

$$G_t - \lambda G_{n-1} + \mu G_n = 0, \tag{3.23}$$

$$G_{n+1} - F_n - \lambda G_n = 0, \tag{3.24}$$

$$\lambda G_{n-1} + G_n + \gamma F_n = 0, \tag{3.25}$$

When we take $\lambda = 2, \mu = 3, \gamma = 3$ we can obtain the following solution of (2.2)-(2.3)

$$F_n = (2/3)^{n+1} - 2(2/3)^n - e^{-t}, \quad G_n = (2/3)^n + e^{-t}. \tag{3.26}$$

In Fig. 1, we plot the one-soliton solution for u and v respectively.

4 Integrable full-discrete version of the RTL

We propose the following bilinear equations

$$[-\frac{1}{\epsilon}\sinh(\epsilon D_t)e^{-\frac{D_m+D_n}{2}} - e^{-\frac{D_m+D_n}{2}+\epsilon D_t} + e^{\frac{D_m-D_n}{2}-\epsilon D_t}]f \bullet f = 0, \tag{4.1}$$

$$[-\frac{1}{\epsilon}\sinh(\epsilon D_t)e^{-\frac{D_m}{2}} + e^{-\frac{D_m}{2}-\epsilon D_t} - e^{\frac{D_m}{2}-D_n-\epsilon D_t}]f \bullet f = 0. \tag{4.2}$$

In the continuum limit as $\epsilon \to 0$, the system (4.1) and (4.2) reduces to the lattice (3.2) and (3.3). The system (4.1) and (4.2) therefore provides a fully discrete version of (3.2) and (3.3).



$(a)\quad u_n$ $(b)\quad v_n$

Fig. 1: (Color online) The one-soliton solution for (1.10)-(1.11): $n = 4$.

Note that

$$F = f_{m+\frac{1}{2}}, \quad G = f_{m-\frac{1}{2}}, \tag{4.3}$$

and denote the variable t as k, Eqs. (4.1)-(4.2) can be rewritten as

$$(-\frac{1}{2\epsilon} - 1)G_n^{k+1}F_{n+1}^{k-1} + \frac{1}{2\epsilon}G_n^{k-1}F_{n+1}^{k+1} + G_{n+1}^{k+1}F_n^{k-1} = 0, \tag{4.4}$$

$$(\frac{1}{2\epsilon} + 1)G_n^{k-1}F_n^{k+1} - \frac{1}{2\epsilon}G_n^{k+1}F_n^{k-1} - G_{n+1}^{k+1}F_{n-1}^{k-1} = 0. \tag{4.5}$$

With the dependent variable transformation

$$u_n^k = \frac{G_{n-1}^k}{F_n^k}, \quad v_n^k = \frac{F_n^k}{G_n^k}, \tag{4.6}$$

the bilinear equations (4.4)-(4.5) are put in the following nonlinear form:

$$(-\frac{1}{2\epsilon} - 1)u_{n+1}^{k+1}v_{n+1}^{k+1} + u_{n+1}^{k-1}v_n^{k-1} + \frac{1}{2\epsilon}u_{n+1}^{k-1}v_{n+1}^{k+1} = 0, \tag{4.7}$$

$$(\frac{1}{2\epsilon} + 1)v_n^{k+1}u_{n+1}^{k+1}v_{n+1}^{k+1} - \frac{1}{2\epsilon}v_n^{k-1}u_{n+1}^{k+1}v_{n+1}^{k+1} - u_n^{k-1}v_{n-1}^{k-1}v_n^{k-1} = 0. \tag{4.8}$$

Set $t = k\epsilon$. By using the Taylor formula,

$$u_n^{k+1} = u_n((k+1)\epsilon) = u_n(t+\epsilon) = u_n(t) + u_n'(t)\epsilon + \mathcal{O}(\epsilon^2) \tag{4.9}$$

and after careful calculations, we finally obtain that as $\epsilon \to 0$ the continuum limits of the fully discrete Eqs. (4.7) and (4.8) are given by

$$u_n' = u_n\left(\frac{v_{n-1}}{v_n} - 1\right), \tag{4.10}$$

$$v_n' = v_n\left(\frac{u_n v_{n-1}}{u_{n+1}v_{n+1}} - 1\right). \tag{4.11}$$

Setting $d_n = (\ln u_n)' + 1$ and $c_n = (\ln v_n)' + 1$, then we get

$$d_n' = d_n(c_{n-1} - c_n), \tag{4.12}$$

$$c_n' = c_n(c_{n-1} - c_{n+1} + d_n - d_{n+1}), \tag{4.13}$$

which is just the RT system (1.10) and (1.11). Therefore the system (4.7) and (4.8) provides a fully discrete version of the potential RT system.

When we take the dependent variable transformation

$$U_n^k = \frac{F_n^{k-1}G_{n-1}^{k+1}}{F_n^{k+1}G_{n-1}^{k-1}} = \frac{u_n^{k+1}}{u_n^{k-1}}, \quad V_n^k = \frac{F_n^{k+1}G_n^{k-1}}{F_n^{k-1}G_n^{k+1}} = \frac{v_n^{k+1}}{v_n^{k-1}}, \tag{4.14}$$

we can deduce from (4.1)-(4.2) that

$$(1+\frac{1}{2\epsilon})(U_n^{k+1}-U_n^{k-1}) = \frac{v_{n-1}^k}{v_n^{k+2}} - \frac{v_{n-1}^{k-2}}{v_n^k}, \tag{4.15}$$

$$(1+\frac{1}{2\epsilon})(V_n^{k+1}-V_n^{k-1}) = \frac{u_n^k v_{n-1}^k}{u_{n+1}^{k+2}v_{n+1}^{k+2}} - \frac{u_n^{k-2}v_{n-1}^{k-2}}{u_{n+1}^k v_{n+1}^k}. \tag{4.16}$$

One can check that in the continuum limit $\epsilon \to 0$, Eqs. (4.15)-(4.16) reduce to the RTL equation

$$U_n' = U_n(V_{n-1} - V_n), \tag{4.17}$$

$$V_n' = V_n(V_{n-1} - V_{n+1} + U_n - U_{n+1}). \tag{4.18}$$

Hence equations (4.14)-(4.16) give a fully discrete version of the RT system (1.10) and (1.11).

Remark 4.1 *We remark here that the full discrete analogue of RTL obtained here is different from* (1.17). *Suris obtained dRTL by using Hamiltonian method, while here we start from Hirota bilinear method. What interesting for integrable discretization is that one integrable system may have some different integrable discrete analogues. Among these integrable discrete versions, some are linked each other by appropriate transformations. Others may have no direct relation. In our case, we have not found the direct link between our full discrete RTL to* (1.17).

For simplicity we take $\epsilon = 1$ in the following. In this case, the bilinear system (4.1)-(4.2) and nonlinear equations (4.7)-(4.8) become

$$(e^{\frac{D_m - D_n}{2} - D_k} - \frac{3}{2}e^{-\frac{D_m + D_n}{2} + D_k} + \frac{1}{2}e^{-\frac{D_m + D_n}{2} - D_k})f \bullet f = 0, \tag{4.19}$$

$$(e^{\frac{D_m}{2} - D_n - D_k} + \frac{1}{2}e^{-\frac{D_m}{2} + D_k} - \frac{3}{2}e^{-\frac{D_m}{2} - D_k})f \bullet f = 0, \tag{4.20}$$

and

$$u_{n+1}^{k-1}v_n^{k-1} - \frac{3}{2}u_{n+1}^{k+1}v_{n+1}^{k+1} + \frac{1}{2}u_{n+1}^{k-1}v_{n+1}^{k+1} = 0, \tag{4.21}$$

$$u_n^{k-1}v_{n-1}^{k-1}v_n^{k-1} + \frac{1}{2}v_n^{k-1}u_{n+1}^{k+1}v_{n+1}^{k+1} - \frac{3}{2}v_n^{k+1}u_{n+1}^{k+1}v_{n+1}^{k+1} = 0. \tag{4.22}$$

respectively.

We will show that (4.21)-(4.22) is integrable by exhibiting its BT and Lax pair. Concerning the bilinear equations (4.19)-(4.20), we have the following result:

Proposition 4.1 *The bilinear equations (4.19)-(4.20) have the Bäcklund transformation*

$$(e^{\frac{D_m}{2}} + \gamma e^{-\frac{D_m}{2}} - 2\mu e^{\frac{D_m}{2} - D_n})f \bullet g = 0, \tag{4.23}$$

$$(e^{\frac{D_n}{2} + D_k} + \lambda e^{-\frac{D_n}{2} - D_k} + \mu e^{-\frac{D_n}{2} + D_k})f \bullet g = 0, \tag{4.24}$$

$$(e^{\frac{D_m + D_n}{2}} + \frac{2}{3}\mu e^{\frac{D_m - D_n}{2}} + \alpha e^{-\frac{D_m + D_n}{2}})f \bullet g = 0. \tag{4.25}$$

where λ, μ, γ *and* α *are arbitrary constants.*

Proof. Let f be a solution of equations (4.19)-(4.20). If it can be shown that g given by (4.23)-(4.25) satisfies

$$
\begin{aligned}
P_1 &\equiv (e^{\frac{D_m-D_n}{2}-D_k} - \frac{3}{2}e^{-\frac{D_m+D_n}{2}+D_k} + \frac{1}{2}e^{-\frac{D_m+D_n}{2}-D_k})g\bullet g = 0,\\
P_2 &\equiv (e^{\frac{D_m}{2}-D_n-D_k} + \frac{1}{2}e^{-\frac{D_m}{2}+D_k} - \frac{3}{2}e^{-\frac{D_m}{2}-D_k})g\bullet g = 0,
\end{aligned}
$$

then the equations (4.23)-(4.25) provide a BT for (4.19)-(4.20).

In fact, by using (4.23)-(4.25) and the bilinear identities, one can see that

$$
\begin{aligned}
&-[e^{-\frac{D_m+D_n}{2}-D_k}f\bullet f]P_1\\
&\equiv [(e^{\frac{D_m-D_n}{2}-D_k} - \frac{3}{2}e^{-\frac{D_m+D_n}{2}+D_k} + \frac{1}{2}e^{-\frac{D_m+D_n}{2}-D_k})f\bullet f][e^{-\frac{D_m+D_n}{2}-D_k}g\bullet g]\\
&\qquad\qquad - [e^{\frac{D_m-D_n}{2}-D_k} - \frac{3}{2}e^{-\frac{D_m+D_n}{2}+D_k} + \frac{1}{2}e^{-\frac{D_m+D_n}{2}-D_k})g\bullet g][e^{-\frac{D_m+D_n}{2}-D_k}f\bullet f]\\
&= 2\sinh(\frac{D_m}{2})(e^{-\frac{D_n}{2}-D_k}f\bullet g)\bullet(e^{\frac{D_n}{2}+D_k}f\bullet g) - 3\sinh(D_k)(e^{-\frac{D_n+D_m}{2}}f\bullet g)\bullet(e^{\frac{D_m+D_n}{2}}f\bullet g)\\
&= -2\mu\sinh(\frac{D_m}{2})(e^{-\frac{D_n}{2}-D_k}f\bullet g)\bullet(e^{-\frac{D_n}{2}+D_k}f\bullet g) - 3\sinh(D_k)(e^{-\frac{D_n+D_m}{2}}f\bullet g)\bullet(e^{\frac{D_m+D_n}{2}}f\bullet g)\\
&= 2\mu\sinh(D_k)[e^{\frac{D_m-D_n}{2}}f\bullet g]\bullet(e^{-\frac{D_m+D_n}{2}}f\bullet g) - 3\sinh(D_k)(e^{-\frac{D_n+D_m}{2}}f\bullet g)\bullet(e^{\frac{D_m+D_n}{2}}f\bullet g)\\
&= -3\sinh(D_k)(e^{-\frac{D_m+D_n}{2}}f\bullet g)\bullet[(e^{\frac{D_m+D_n}{2}} + \frac{2}{3}\mu e^{\frac{D_m-D_n}{2}})f\bullet g]\\
&= 0
\end{aligned}
$$

and similarly that

$$
\begin{aligned}
&-[e^{-\frac{D_m}{2}-D_k}f\bullet f]P_2\\
&\equiv [(e^{\frac{D_m}{2}-D_n-D_k} + \frac{1}{2}e^{-\frac{D_m}{2}+D_k} - \frac{3}{2}e^{-\frac{D_m}{2}-D_k})f\bullet f][e^{-\frac{D_m}{2}-D_k}g\bullet g]\\
&\qquad\qquad - [(e^{\frac{D_m}{2}-D_n-D_k} + \frac{1}{2}e^{-\frac{D_m}{2}+D_k} - \frac{3}{2}e^{-\frac{D_m}{2}-D_k})g\bullet g][e^{-\frac{D_m}{2}-D_k}f\bullet f]\\
&= 2\sinh(\frac{D_m-D_n}{2})(e^{-\frac{D_n}{2}-D_k}f\bullet g)\bullet(e^{\frac{D_n}{2}+D_k}f\bullet g) + \sinh(D_k)(e^{-\frac{D_m}{2}}f\bullet g)\bullet(e^{\frac{D_m}{2}}f\bullet g)\\
&= -2\mu\sinh(\frac{D_m-D_n}{2})(e^{-\frac{D_n}{2}-D_k}f\bullet g)\bullet(e^{-\frac{D_n}{2}+D_k}f\bullet g) + \sinh(D_k)(e^{-\frac{D_m}{2}}f\bullet g)\bullet(e^{\frac{D_m}{2}}f\bullet g)\\
&= 2\mu\sinh(D_k)(e^{\frac{D_m}{2}-D_n}f\bullet g)\bullet(e^{-\frac{D_m}{2}}f\bullet g) + \sinh(D_k)(e^{-\frac{D_m}{2}}f\bullet g)\bullet(e^{\frac{D_m}{2}}f\bullet g)\\
&= \sinh(D_k)(e^{-\frac{D_m}{2}}f\bullet g)\bullet[(e^{\frac{D_m}{2}} - 2\mu e^{\frac{D_m}{2}-D_n})f\bullet g]\\
&= 0.
\end{aligned}
$$

This completes the proof of proposition 4.1. Again we can obtain from Proposition 3.1 that the bilinear fully discrete RT lattice (4.4)-(4.5) ($\epsilon = 1$) has the following BT:

$$
\begin{aligned}
&F_nG'_n + \gamma G_nF'_n - 2\mu F_{n-1}G'_{n+1} = 0, && (4.26)\\
&F_{n+1}G'_n + \frac{2}{3}\mu F_nG'_{n+1} + \alpha G_nF'_{n+1} = 0, && (4.27)\\
&F_{n+1,k+1}F'_{n,k-1} + \lambda F_{n,k-1}F'_{n+1,k+1} + \mu F_{n,k+1}F'_{n+1,k-1} = 0, && (4.28)\\
&G_{n+1,k+1}G'_{n,k-1} + \lambda G_{n,k-1}G'_{n+1,k+1} + \mu G_{n,k+1}G'_{n+1,k-1} = 0. && (4.29)
\end{aligned}
$$

Using (4.26)-(4.29), we can obtain a nontrivial solution from the trivial solution. It is easy to check that

$F' = G' = 1$ is a solution of (4.4)-(4.5). Substituting this trivial solution into the BT (4.26)-(4.29), we have

$$F_n + \gamma G_n - 2\mu F_{n-1} = 0, \tag{4.30}$$

$$F_{n+1} + \frac{2}{3}\mu F_n + \alpha G_n = 0, \tag{4.31}$$

$$F_{n+1}^{k+1} + \lambda F_n^{k-1} + \mu F_n^{k+1} = 0, \tag{4.32}$$

$$G_{n+1}^{k+1} + \lambda G_n^{k-1} + \mu G_n^{k+1} = 0. \tag{4.33}$$

When we take $\alpha = 11\gamma, \mu = 1, \lambda = -100$, we get the following solution of (4.30)-(4.33)

$$F_n = c_1 5^k 3^n + c_2(\sqrt{12})^k (\frac{22}{3})^n, \tag{4.34}$$

$$G_n = 2\left[c_1 5^k 3^{n-1} + c_2(\sqrt{12})^k(\frac{22}{3})^{n-1}\right] - c_1 5^k 3^n - c_2(\sqrt{12})^k(\frac{22}{3})^n. \tag{4.35}$$

c_1 and c_2 are arbitrary constants. In Fig. 2, we plot the one-soliton solution for U_n^k and V_n^k by use of (4.14) with parameters selected as $c_1 = 2, c_2 = 1$ and $k = 5$.



$(a)\quad U_n^k$ $\qquad$ $(b)\quad V_n^k$

Fig. 2: (Color online) The one-soliton solution for full-discrete system (4.14)-(4.16).

In the following, we derive a Lax pair for the fully discrete RTL (4.21)-(4.22). Let

$$\frac{F'_n}{G'_n} = v_n, \quad \frac{G'_{n-1}}{F'_n} = u_n, \quad \frac{F}{F'} = \Phi, \quad \frac{G}{G'} = \Psi. \tag{4.36}$$

From Eqs. (4.26)-(4.29) we get

$$\Phi_n u_{n+1} v_{n+1} + \gamma \Psi_n u_{n+1} v_{n+1} - 2\mu \Phi_{n-1} u_n v_{n-1} = 0, \tag{4.37}$$

$$\Phi_{n+1} v_{n+1} + \alpha \Psi_n v_{n+1} + \frac{2}{3}\mu \Phi_n v_n = 0, \tag{4.38}$$

$$\Phi_{n+1}^{k+1} u_{n+1}^{k-1} v_n^{k-1} + \lambda \Phi_n^{k-1} u_{n+1}^{k-1} v_n^{k-1} + \mu \Phi_n^{k+1} u_{n+1}^{k+1} v_n^{k+1} = 0, \tag{4.39}$$

$$\Psi_{n+1}^{k+1} u_{n+1}^{k-1} v_{n+1}^{k-1} + \lambda \Psi_n^{k-1} u_{n+1}^{k-1} v_{n+1}^{k-1} + \mu \Psi_n^{k+1} u_{n+1}^{k+1} v_{n+1}^{k+1} = 0. \tag{4.40}$$

In order to obtain a Lax pair for (4.21) and (4.22), we first use (4.38) to express Ψ in (4.40) in terms of Φ and then to write Φ_{n+2} and Φ_{n+1} as expressions of Φ_n. After some calculations we find

$$\begin{aligned} &-2u_{n+1}^{k-1} u_{n+2}^{k-1} v_{n+1}^{k-1} v_{n+1}^{k+1} + 2u_{n+1}^{k-1} u_{n+2}^{k-1} v_n^{k-1} v_{n+2}^{k+1} \\ &\quad -3u_{n+1}^{k+1} u_{n+2}^{k-1} v_{n+1}^{k+1} v_{n+2}^{k+1} + 3u_{n+1}^{k-1} u_{n+2}^{k+1} v_{n+1}^{k+1} v_{n+2}^{k+1} = 0, \end{aligned} \tag{4.41}$$

or

$$\begin{aligned} &\frac{2u_{n+2}^{k-1} v_{n+1}^{k-1} - 3u_{n+2}^{k+1} v_{n+2}^{k+1}}{u_{n+2}^{k-1} v_{n+2}^{k+1}} - \frac{2u_{n+1}^{k-1} v_n^{k-1} - 3u_{n+1}^{k+1} v_{n+1}^{k+1}}{u_{n+1}^{k-1} v_{n+1}^{k+1}} \\ &= (E_n - 1)\frac{2u_{n+1}^{k-1} v_n^{k-1} - 3u_{n+1}^{k+1} v_{n+1}^{k+1}}{u_{n+1}^{k-1} v_{n+1}^{k+1}} = 0. \end{aligned} \tag{4.42}$$

It follows that

$$\frac{2u_{n+1}^{k-1}v_n^{k-1} - 3u_{n+1}^{k+1}v_{n+1}^{k+1}}{u_{n+1}^{k-1}v_{n+1}^{k+1}} = -c, \tag{4.43}$$

or equivalently,

$$2u_{n+1}^{k-1}v_n^{k-1} - 3u_{n+1}^{k+1}v_{n+1}^{k+1} + cu_{n+1}^{k-1}v_{n+1}^{k+1} = 0. \tag{4.44}$$

Setting $u_n^k \to c^{-k/2}u_n^k, v_n^k \to c^{k/2}v_n^k$, we have

$$2u_{n+1}^{k-1}v_n^{k-1} - 3u_{n+1}^{k+1}v_{n+1}^{k+1} + u_{n+1}^{k-1}v_{n+1}^{k+1} = 0, \tag{4.45}$$

which coincides with (4.21). Similarly, combining (4.37) and (4.39), we get

$$\begin{aligned}&-2u_{n+1}^{k-1}u_{n+1}^{1+k}v_n^{k-1}v_n^{1+k}v_{n+1}^{k-1} + 2u_n^{k-1}u_{2+n}^{1+k}v_{n-1}^{k-1}v_n^{k-1}v_{2+n}^{1+k}\\ &\qquad -u_{1+n}^{1+k}u_{2+n}^{1+k}v_n^{1+k}v_{n+1}^{k-1}v_{2+n}^{1+k} + u_{1+n}^{1+k}u_{2+n}^{1+k}v_n^{k-1}v_{1+n}^{1+k}v_{2+n}^{1+k} = 0,\end{aligned} \tag{4.46}$$

or

$$\begin{aligned}&\frac{\left(2u_{n+1}^{k-1}v_n^{k-1} + u_{2+n}^{1+k}v_{2+n}^{1+k}\right)v_{n+1}^{k-1}}{u_{2+n}^{1+k}v_{2+n}^{1+k}v_{n+1}^{k+1}} - \frac{\left(2u_n^{k-1}v_{n-1}^{k-1} + u_{1+n}^{1+k}v_{1+n}^{1+k}\right)v_n^{k-1}}{u_{1+n}^{1+k}v_{n+1}^{k+1}v_n^{1+k}}\\ &= (E_n - 1)\frac{\left(2u_n^{k-1}v_{n-1}^{k-1} + u_{1+n}^{1+k}v_{1+n}^{1+k}\right)v_n^{k-1}}{u_{1+n}^{1+k}v_{n+1}^{k+1}v_n^{1+k}} = 0.\end{aligned} \tag{4.47}$$

We then have

$$\frac{\left(2u_n^{k-1}v_{n-1}^{k-1} + u_{1+n}^{1+k}v_{1+n}^{1+k}\right)v_n^{k-1}}{u_{1+n}^{1+k}v_{n+1}^{k+1}v_n^{1+k}} = 3c, \tag{4.48}$$

or

$$\left(2u_n^{k-1}v_{n-1}^{k-1} + u_{n+1}^{k+1}v_{n+1}^{k+1}\right)v_n^{k-1} - 3cu_{n+1}^{k+1}v_{n+1}^{k+1}v_n^{k+1} = 0. \tag{4.49}$$

Setting $u_n^k \to c^{k/2}u_n^k, v_n^k \to c^{-k/2}v_n^k$, we arrive at

$$\left(2u_n^{k-1}v_{n-1}^{k-1} + u_{n+1}^{k+1}v_{n+1}^{k+1}\right)v_n^{k-1} - 3u_{n+1}^{k+1}v_{n+1}^{k+1}v_n^{k+1} = 0. \tag{4.50}$$

which checks with (4.22). So Eqs.(4.37)-(4.40) constitute the Lax pair for (4.21)-(4.22).

5 Conclusion

In this paper we present a bilinear form for a integrable lattice related to the well-known relativistic Toda lattice. Through Hirota's bilinear integrable discretization method a fully discrete version of the lattice is obtained. Bilinear BT and Lax pair for both the original and the fully discrete lattice are investigated.

Acknowledgements

The authors would like to express their thanks to the referees for valuable advice. G.Yu and Y.Zhang are grateful to Xing-Biao Hu for helpful discussions. The work of L.V. is supported by a grant from the National Science and Engineering Research Council (NSERC) of Canada. G.Yu acknowledges a postdoctoral fellowship from the CRM of Mathematical Physics Laboratory. G.Yu and Y.Zhang are also supported by the National Natural Science Foundation of China (Grant no.11371251,11271362) and Chenguang Program (No.09CG08) sponsored by Shanghai Municipal Education Commission and Shanghai Educational Development Foundation.

References

[1] Bruschi M, Ragnisco O 1988 Recursion operator and Bäcklund transformations for the Ruijsenaars-Toda lattice. Phys. Lett. A **129** 21-25

[2] Oevel W, Fuchssteiner B, H.W Zhang, and O.Ragnisco 1989 Mastersymmetries, angle variables, and recursion operator of the relativistic Toda lattice, J. Math. Phys. **30** 2664-2670

[3] S. N. M. Ruijsenaars, Commun. Math. Phys. 133 (1990) 217.

[4] Common A K and Hafezt S T 1992 Linearization of the relativistic and discrete-time Toda lattices for particular boundary conditions, Inverse Problems **8** 59-69.

[5] Suris Y B 1997 New integrable systems related to the relativistic Toda lattice, J. Phys. A: Math. Gen. **30** 1745-1761

[6] Ma W-X, Xu X-X 2004 Positive and negative hierarchies of integrable lattice models associated with a Hamiltonian pair, Int. J. Theor. Phys. **43** 219-235.

[7] Fan E-G, Dai H-H 2008 A differential-difference hierarchy associated with relativistic Toda and Volterra hierarchies, Phys. Lett. A **372** 4578-4585

[8] Wen X-Y 2011 New hierarchies of integrable lattice equatioins and associated properties: darboux transformation, conservation laws and integrable copling, Rep. Math. Phys. **67** 259-277

[9] Ohta Y, Kajiwara K, Matsukidaira J, Satsuma J 1993 Casorati determinant solution for the relativistic Toda lattice equation, J. Math. Phys. **34** 5190-5204

[10] Kharchev S, Mironov A, Zhedanov A 1996 Faces of relativistic Toda chain, Int.J.Mod.Phys. **A12**, 2675-2724. (arXiv:hep-th/9606144)

[11] Vinet L and Zhedanov A 1998 An integrable chain and bi-orthogonal polynomials, Lett. Math. Phys. **46** 233-245

[12] Suris Y B 1996 A discrete-time relativistic Toda lattice. J.Phys.A: Math. and Gen., **29** 451-465

[13] Zhu Z.N., Huang H.C. and Xue W.M. 1999 New Lax representation and integrable discretization of the relativistic Volterra lattice. J. Phys. Soc. Japan **68** 771-775

[14] Maruno K, Kajiwara K, Oikawa M 1998 Casorati determinant solution for the discrete-time relativistic Toda lattice equation, Phys. Lett. A **241** 335-343

[15] Tsujimoto S, Zhedanov A 2009 Elliptic hypergeometric Laurent biorthogonal polynomials with a dense point spectrum on the unit circle, SIGMA Symmetry Integrability Geom. Methods Appl. **5** 033

[16] Levi D, Vinet L and Winternitz P (ed.) 1996 Symmetries and Integrability of Difference Equations, CRM Proceedings & Lecture Notes, Vol. **9**, American Mathematical Society

[17] Clarkson P A and Nijhoff F W (ed.) 1999 Symmetries and Integrability of Difference Equations, London Mathematical Society Lecture Note Series 255, Cambridge, New York, Cambridge University Press,

[18] Levi D and Ragnisco O (ed.) 2000 SIDE III–Symmetries and Integrability of Difference Equations, CRM Proceedings & Lecture Notes, Vol. **25**, American Mathematical Society

[19] Hietarinta J, Nijhoff F W and Satsuma J (ed.) 2001 Symmetries and integrability of difference equations, Institute of Physics Publishing, Bristol, **34** 10337-10744

[20] Suris Y B 2003 The problem of integrable discretization: Hamiltonian approach. Progress in Mathematics, 219. Birkhäuser Verlag, Basel.

[21] Hirota R 1977 Nonlinear partial difference equations. I. A difference analogue of the Korteweg-de Vries equation. J. Phys. Soc. Japan. **43** 1424-1433

[22] Hirota R 1977 Nonlinear partial difference equations. II. Discrete-time Toda equation. J. Phys. Soc. Japan. **43** 2074-2078

[23] Hirota R 1977 Nonlinear partial difference equations. III. Discrete sine-Gordon equation. J. Phys. Soc. Japan. **43** 2079-2086

[24] Hirota R 1978 Nonlinear partial difference equations. IV. Bäcklund transformations for the discrete-time Toda equation. J. Phys. Soc. Japan. **45** 1321-1332

[25] R.Hirota 1981 Discrete analogue of a generalized Toda equation. J. Phys. Soc. Japan. **50** 3785-3791

[26] Hirota R, Iwao R, Time-discretization of soliton equations. SIDE III—symmetries and integrability of difference equations (Sabaudia, 1998), 217–229, CRM Proc. Lecture Notes, 25, Amer. Math. Soc., Providence, RI,(2000)

[27] Hu X-B, Yu G-F 2007 Integrable discretizations of the $(2+1)$-dimensional sinh-Gordon equation, J. Phys. A **40** 12645-12659

[28] Hu X-B, Yu G-F 2009 Integrable semi-discretizations and full-discretization of the two-dimensional Leznov lattice, J. Difference Equ. Appl. **15** 233-252

[29] Ohta Y, Maruno K, B.F Feng 2008 An integrable semi-discretization of the Camassa-Holm equation and its determinant solution, J. Phys. A **41** 355205

[30] B.F. Feng, Maruno K, Ohta Y 2010 Integrable discretizations of the short pulse equation, J. Phys. A **43** , 085203

[31] Hirota R 1980 Direct method in soliton theory, edited by R.K.Bullough and P.J.Caudrey, Springer, Berlin.

[32] Miura R M 1976 Bäcklund transformations, the inverse scattering method, solitons, and their applications. Lecture Notes in Mathematics, Vol. 515. Springer-Verlag, Berlin-New York.

[33] Rogers C, Shadwick W F 1982 Bäcklund transformations and their applications. Mathematics in Science and Engineering, 161. Academic Press, Inc., New York-London.

[34] Rogers C, Schief W K 2002 Bäcklund and Darboux transformations. Geometry and modern applications in soliton theory. Cambridge Texts in Applied Mathematics. Cambridge University Press, Cambridge.

[35] Hu X-B 1994 Nonlinear superposition formulae for the differential-difference analogue of the KdV equation and two-dimensional Toda equation. J. Phys. A: Math. Gen. **27** 201-214